
Database Media Transfer

DBMT messages

DBMT0001	Unable to determine default floppy device name.
DBMT0002	Unable to determine floppy device name.
DBMT0003	Unable to determine file names for transfer.
DBMT0004	Unable to open floppy drive. Action: Be sure disk is properly inserted.
DBMT0005	Unable to create temporary database file.
DBMT0006	Unable to create temporary Configuration file.
DBMT0007	Unable to transfer database to hard disk.
DBMT0008	Unable to append Database and Configuration files into one file.
DBMT0009	Unable to rename Configuration file to Database file for s option.
DBMT0010	Unable to restore file to original state.
DBMT0011	Unable to rename all files correctly.
DBMT0012	Unable to read Private sector from floppy disk.
DBMT0013	Too many disks being used.
DBMT0014	Incorrect disk in drive.
DBMT0015	Unable to identify record type.
DBMT0016	Unable to read sector(s) from disk.

Action: Ensure disk is properly inserted. Check the power and the SCSI cable on the CMDU.

DBMT0017 Unable to write database file to hard disk.

DBMT0018 Unable to write Configuration file to hard disk.

DBMT0019 x y Incorrect database record count. Was x, should be y.

DBMT0020 x y Incorrect Configuration record. Was x, should be y.

DBMT0021 Incorrect floppy disk in drive. Need A1.

DBMT0022 Read Private Sector: Unable to read sector from floppy disk.

DBMT0023 Read Private Sector: Invalid floppy disk.

DBMT0024 Read Private Sector: End of track 1 not found.

DBMT0026 Get Record Type: Unable to identify record type.

DBMT0027 Unused message.

DBMT0028 Get Disk Buffer: Unable to seek on floppy disk.

DBMT0029 Get Disk Buffer: Unable to read from floppy disk.

Action: Check hard disk power, and SCSI cable on CMDU.

DBMT0030 Append Database: Unable to seek database on hard disk.

DBMT0031 Append Database: Unable to seek Configuration on hard disk.

DBMT0032 Append Database: Unable to read from hard disk.

Action: Check hard disk power, and SCSI cable on CMDU.

DBMT0033 Append Database: Unable to write to hard disk.

DBMT0034 Write Database: Unable to write to hard disk.

DBMT0035 Write Database: Unable to write to hard disk.

Action: Check hard disk power, and SCSI cable on CMDU.

DBMT0036 Write Database: Unknown database format.

Action: Be sure that the correct B disk is in the drive.

DBMT0037	Get Directory: Unable to read Private sector from floppy disk.
DBMT0038	Get Directory: Unable to read sector(s) from floppy disk. Action: Be sure disk is inserted properly in the correct drive.
DBMT0039	Close Files: Unable to close floppy device.
DBMT0040	Close Files: Unable to close Database file.
DBMT0041	Close Files: Unable to close Configuration file.
DBMT0042	Rename All Files: Unable to rename secondary Database file to holding file.
DBMT0043	Rename All Files: Unable to restore files to original state.
DBMT0044	Rename All Files: Unable to rename secondary Configuration file to holding file.
DBMT0045	Rename All Files: Unable to rename primary Database file to secondary file.
DBMT0046	Rename All Files: Unable to rename primary Configuration file to secondary file.
DBMT0047	Rename All Files: Unable to rename new Database file to primary file.
DBMT0048	Rename All Files: Unable to rename new Configuration file to primary file.
DBMT0049	Get File Names: Unable to determine primary Database file name.
DBMT0050	Get File Names: Unable to determine secondary Database file name.
DBMT0051	Get File Names: Unable to determine holding Database file name.
DBMT0052	Get File Names: Unable to determine temporary Database file name.
DBMT0053	Get File Names: Unable to determine primary Configuration file name.
DBMT0054	Get File Names: Unable to determine secondary Configuration file name.
DBMT0055	Get File Names: Unable to determine holding Configuration file name.
DBMT0056	Get File Names: Unable to determine temporary Configuration file name.
DBMT0057	Restore Files: Unable to restore temporary Database file.
DBMT0058	Restore Files: Unable to restore primary Database file.
DBMT0059	Restore Files: Unable to restore secondary Database file.

DBMT

DBMT0060	Restore Files: Unable to restore temporary Configuration file.
DBMT0061	Restore Files: Unable to restore primary Configuration file.
DBMT0062	Restore Files: Unable to restore secondary Configuration file.
DBMT0063	Unable to initialize floppy driver to 2 Mb on side x. Action: Be sure CMDU power is on, and cables are in place.
DBMT0064	Unable to initialize floppy driver to 4 Mb on side x. Action: Be sure CMDU power is on, and cables are in place.
DBMT0205	Read Private Sector: End of track 3 not found.